# ESXi 5.x Image Customization Information

Dell Engineering
December 2014

Copyright © 2014 Dell Inc. All rights reserved. This product is protected by U.S. and international copyright and intellectual property laws. Dell™ and the Dell logo are trademarks of Dell Inc. in the United States and/or other jurisdictions. All other marks and names mentioned herein may be trademarks of their respective companies.

Rev. A12

# Table of contents


1 Introduction ..... 4
1.1 Downloading the Dell-customized ESXi image ..... 4
1.2 Write to us ..... 4
1.3 Related links ..... 4
2 ESXi 5.5 Update 2 image customization details ..... 5
Older revisions for ESXi 5.5 Update 2 ..... 5
3 ESXi 5.5 Update 1 image customization details ..... 7
Older revisions for ESXi 5.5 Update 1 ..... 7
4 ESXi 5.5 image customization details ..... 9
Older revisions for ESXi 5.5 ..... 9
5 ESXi 5.1 Update 3 image customization details ..... 12
6 ESXi 5.1 Update 2 image customization details ..... 13
Older revisions for ESXi 5.1 Update 2 ..... 13
7 ESXi 5.1 Update 1 image customization details ..... 18
Older revisions for ESXi 5.1 Update 1 ..... 18
8 ESXi 5.1 image customization details ..... 22
Older revisions for ESXi 5.1 ..... 22
9 ESXi 5.0 Update 3 Iimage customization details ..... 24
10 ESXi 5.0 Update 2 image customization details ..... 25
Older revisions for ESXi 5.0 Update 2 ..... 25
11 ESXi 5.0 Update 1 image customization details ..... 27
Older revisions for ESXi 5.0 Update 1 ..... 27
12 ESXi 5.0 image customization details ..... 30
Older revisions for ESXi 5.0 ..... 30

# 1 Introduction

Each ESXi image is a customization of the base VMware image of a particular version. Dell customization of the image includes:

- Modifying files to identify Dell and Dell support.
- Updating the ESXi image with the latest validated asynchronous drivers.
- Updating patches if it addresses a common issue for Dell systems.

It is recommended to use the latest version of the Dell-customized ESXi image for your Dell system.

**Note:** The Dell-customized ESXi Embedded ISO image does not include Dell OpenManage Server Administrator. For information on installing and using Dell OpenManage Server Administrator, see the Dell OpenManage documentation at **dell.com/openmanagemanuals**.

Additional Dell VMware documents are available at **dell.com/virtualizationsolutions**.

## 1.1 Downloading the Dell-customized ESXi image

Go to **vmware.com/support** and see the Images and Drivers VMware pages for downloading the base ESXi image and the updated driver VIBs that are used for the creation of the ISOs. Your VMware administrator needs to sign in for access to the pages.

To download the Dell-customized ESXi ISO images:

1. Navigate to **dell.com/support**.
2. Enter your system service tag, and click **Submit**.
3. In the Product Support window, click **Drivers & Downloads**.
4. In Drivers and Downloads, click the link **Click here for other operating system**.
5. From the operating system drop down, select the ESXi that you have installed.
6. You will see a list of categories, click **Enterprise**.
7. Download **VMware ESXi 5.x**.

## 1.2 Write to us

For any documentation feedback, write to documentation_feedback@dell.com.

## 1.3 Related links

- Dell Tech Centre for Virtualization
- Drivers and Downloads
- Dell and VMware Product Page
- Dell VMware Documentation

# 2 ESXi 5.5 Update 2 image customization details

Table 1 ESXi 5.5 Update 2 revision A01 image customization details

| | |
|---|---|
| **Version** | A01 |
| **Build Number** | 2068190 |
| **File Name** | VMware-VMvisor-Installer-5.5.0.update02-2068190.x86_64-Dell_Customized-A01.iso |
| **Release Date** | Dec 2, 2014 |
| **Dell Modified Files** | • etc/vmware/oem.xml<br>• etc/vmware/support |
| **Broadcom Drivers** | • tg3 - 3.137d.v55.1<br>• bnx2 - 2.2.5f.v55.6<br>• bnx2x - 2.710.39.v55.2<br>• cnic - 2.710.35.v55.5<br>• cnic-register - 1.710.30.v55.1<br>• bnx2fc - 1.710.35.v55.2<br>• bnx2i - 2.710.30.v55.4 |
| **Intel Drivers** | • igb - 5.2.7<br>• ixgbe - 3.21.4iov |
| **QLogic Drivers** | • qlnativefc - 1.1.29.0<br>• qla4xxx - 644.55.34.0<br>• qlcnic - 5.5.190<br>• qlge - v3.00.00.58 |
| **Emulex Drivers** | • lpfc - 10.2.340.18<br>• elxnet - 10.2.298.5<br>• be2iscsi -10.2.250.0 |
| **Dell Storage Controller Drivers** | • mpt2sas - 19.00.00.00.1vmw<br>• mpt3sas - 04.00.00.00.1vmw<br>• megaraid_perc9- 6.901.55.00.1vmw<br>• megaraid_sas - 06.803.73.00 |
| **Micron Drivers** | mtip32xx_native – 2.13.2 |
| **Mellanox Drivers** | • mlx4_core - 1.9.9.0<br>• mlx4_en - 1.9.9.0 |

**Older revisions for ESXi 5.5 Update 2**

Table 2: ESXi 5.5 Update 2 Revision A00 Image Customization Details

Table 2 ESXi 5.5 Update 2 revision A00 image customization details

| | |
|---|---|
| **Version** | A00 |
| **Build Number** | 2068190 |
| **File Name** | VMware-VMvisor-Installer-5.5.0.update02-2068190.x86_64-Dell_Customized-A00.iso |
| **Release Date** | Sep 9, 2014 |
| **Dell Modified Files** | • etc/vmware/oem.xml<br>• etc/vmware/support |
| **Broadcom Drivers** | • tg3 - 3.136h.v55.1<br>• bnx2 - 2.2.5f.v55.6<br>• bnx2x - 2.710.39.v55.2<br>• cnic - 2.710.35.v55.5<br>• cnic-register - 1.710.30.v55.1<br>• bnx2fc - 1.710.35.v55.1<br>• bnx2i - 2.710.30.v55.4 |
| **Intel Drivers** | • igb - 5.2.5<br>• ixgbe - 3.21.4iov |
| **QLogic Drivers** | • qlnativefc - 1.1.29.0<br>• qla4xxx - 644.55.34.0<br>• qlcnic - 5.5.190<br>• qlge - v3.00.00.58 |
| **Emulex Drivers** | • lpfc - 10.2.340.18<br>• elxnet - 10.2.298.5<br>• be2iscsi -10.2.250.0 |
| **Dell Storage Controller Drivers** | • mpt2sas - 18.00.00.00.1vmw<br>• mpt3sas - 04.00.00.00.1vmw<br>• megaraid_perc9- 6.901.55.00.1vmw<br>• megaraid_sas - 06.803.52.00 |
| **Micron Drivers** | mtip32xx_native - 3.9.4 |
| **Mellanox Drivers** | • mlx4_core - 1.9.9.0<br>• mlx4_en - 1.9.9.0 |

# 3 ESXi 5.5 Update 1 image customization details

Table 3 ESXi 5.5 Update 1 revision A01 image customization details

| | |
|---|---|
| **Product Name** | Dell Customized VMware ESXi 5.5 Update 1 Image |
| **Version** | A01 |
| **Build Number** | 1746018 |
| **File Name** | VMware-VMvisor-Installer-5.5.0.update01-1746018.x86_64-Dell_Customized-A01.iso |
| **Release Date** | July 1, 2014 |
| **Dell Modified Files** | • etc/vmware/oem.xml<br>• etc/vmware/support |
| **Broadcom Drivers** | • tg3 - 3.136e.v55.1<br>• bnx2 - 2.2.4f.v55.3<br>• bnx2x - 1.78.80.v55.3<br>• cnic - 1.78.76.v55.7<br>• cnic-register - 1.78.75.v55.1<br>• bnx2fc - 1.78.76.v55.1<br>• bnx2i - 2.78.76.v55.1 |
| **Intel Drivers** | • igb – 5.2.5<br>• ixgbe - 3.21.4iov |
| **QLogic Drivers** | • qlnativefc - 1.1.20.0-1<br>• qla4xxx - 634.55.28.0<br>• qlcnic - 5.5.183<br>• qlge - v3.00.00.58 |
| **Emulex Drivers** | • lpfc - 10.0.727.44-1<br>• elxnet - 10.0.783.13-1<br>• be2iscsi – 10.0.727.4401 |
| **Dell Storage Controller Drivers** | • mpt2sas - 19.00.00.00.1vmw<br>• megaraid-perc9 - 6.900.50.00.1vmw<br>• megaraid_sas - 06.803.52.00 |
| **Micron Drivers** | • mtip32xx_native - 3.8.2-1 |

**Older revisions for ESXi 5.5 Update 1**

Table 4: ESXi 5.5 Update 1 Revision A00 Image Customization Details

Table 4 ESXi 5.5 Update 1 revision A00 image customization details

| | |
|---|---|
| **Product Name** | Dell Customized VMware ESXi 5.5 Update 1 Image |
| **Version** | A00 |
| **Build Number** | 1746018 |
| **File Name** | VMware-VMvisor-Installer-5.5.0.update01-1746018.x86_64-Dell_Customized-A00.iso |
| **Release Date** | April 29, 2014 |
| **Dell Modified Files** | • etc/vmware/oem.xml<br>• etc/vmware/support |
| **Broadcom Drivers** | • tg3 - 3.136e.v55.1<br>• bnx2 - 2.2.4f.v55.3<br>• bnx2x - 1.78.80.v55.3<br>• cnic - 1.78.76.v55.7<br>• cnic-register - 1.78.75.v55.1<br>• bnx2fc - 1.78.76.v55.1<br>• bnx2i - 2.78.76.v55.1 |
| **Intel Drivers** | • igb – 5.2.5<br>• ixgbe - 3.21.4iov |
| **QLogic Drivers** | • qlnativefc - 1.1.20.0-1<br>• qla4xxx - 634.55.28.0<br>• qlcnic - 5.5.177<br>• qlge - v3.00.00.57 |
| **Emulex Drivers** | • lpfc - 10.0.727.44-1<br>• elxnet - 10.0.727.28-1<br>• be2iscsi – 10.0.727.4401 |
| **Dell Storage Controller Drivers** | • mpt2sas - 18.00.00.00.1vmw<br>megaraid-perc9 - 6.900.50.00.1vmw |
| **Micron Drivers** | • mtip32xx_native - 3.6.9-1 |

# 4 ESXi 5.5 image customization details

Table 5 ESXi 5.5 revision A02 image customization details

| | |
|---|---|
| **Product Name** | Dell Customized VMware ESXi 5.5 Image |
| **Version** | A02 |
| **Build Number** | 1331820 |
| **File Name** | VMware-VMvisor-Installer-5.5.0 1331820.x86_64-Dell_Customized_A02.iso |
| **Release Date** | March 11, 2014 |
| **Dell Modified Files** | • etc/vmware/oem.xml<br>• etc/vmware/support |
| **Broadcom Drivers** | • tg3 - 3.133d.v55.1<br>• bnx2 - 2.2.3t.v55.7<br>• bnx2x - 1.78.28.v55.2<br>• cnic - 1.78.12.v55.6<br>• cnic-register - 1.78.1.v55.7<br>• bnx2fc - 1.78.16.v55.4<br>• bnx2i - 2.78.11.v55.4 |
| **Intel Drivers** | • igb - 4.2.16.8<br>• ixgbe - 3.18.7iov |
| **QLogic Drivers** | • qlnativefc - 1.1.7.0-1OEM.550.0.0.1198610<br>• qla4xxx - 634.55.20.0-1vmw<br>• qlcnic - 5.5.164<br>• qlge - v3.00.00.57 |
| **Emulex Drivers** | • lpfc - 10.0.727.44<br>• elxnet - 10.0.727.28<br>• be2iscsi – 10.0.727.4401 |
| **Dell Storage Controller Drivers** | • mpt2sas - 16.00.01.00.1vmw<br>• megaraid-perc9 - 6.900.50.00.1vmw |

**Older revisions for ESXi 5.5**

Table 6: ESXi 5.5 Revision A01 Image Customization Details

Table 7: ESXi 5.5 Revision A00 Image Customization Details

Table 6 ESXi 5.5 revision A01 image customization details

| | |
|---|---|
| **Product Name** | Dell Customized VMware ESXi 5.5 Image |
| **Version** | A01 |
| **Build Number** | 1331820 |
| **File Name** | VMware-VMvisor-Installer-5.5.0 1331820.x86_64-Dell_Customized_A01.iso |
| **Release Date** | October 4, 2013 |
| **Dell Modified Files** | • etc/vmware/oem.xml<br>• etc/vmware/support |
| **Broadcom Drivers** | • tg3 - 3.133d.v55.1<br>• bnx2 - 2.2.3t.v55.7<br>• bnx2x - 1.78.28.v55.2<br>• cnic - 1.78.12.v55.6<br>• cnic-register - 1.78.1.v55.7<br>• bnx2fc - 1.78.16.v55.4<br>• bnx2i - 2.78.11.v55.4 |
| **Intel Drivers** | • igb - 4.2.16.8<br>• ixgbe - 3.18.7iov |
| **QLogic Drivers** | • qlnativefc - 1.1.7.0-1OEM.550.0.0.1198610<br>• qla4xxx - 634.55.20.0-1vmw<br>• qlcnic - 5.5.164<br>• qlge - v3.00.00.57 |
| **Emulex Drivers** | • lpfc - 10.0.575.8-1OEM.550.0.0.1198611<br>• elxnet - 10.0.575.7-10EM-550.0.0.1198611<br>• be2iscsi - 4.6.261.0 |
| **Dell Storage Controller Drivers** | • mpt2sas - 16.00.01.00.1vmw |

Table 7 ESXi 5.5 revision A00 image customization details

| | |
|---|---|
| **Product Name** | Dell Customized VMware ESXi 5.5 Image |
| **Version** | A00 |
| **Build Number** | 1331820 |
| **File Name** | VMware-VMvisor-Installer-5.5.0-1331820.x86_64-Dell_Customized_A00.iso |
| **Release Date** | October 1, 2013 |
| **Dell Modified Files** | • etc/vmware/oem.xml<br>• etc/vmware/support |
| **Broadcom Drivers** | • tg3 - 3.133d.v55.1<br>• bnx2 - 2.2.3t.v55.7<br>• bnx2x - 1.78.28.v55.2<br>• cnic - 1.78.12.v55.6<br>• cnic-register - 1.78.1.v55.7<br>• bnx2fc - 1.78.16.v55.4<br>• bnx2i - 2.78.11.v55.4 |
| **Intel Drivers** | • igb - 4.2.16.8<br>• ixgbe - 3.18.7iov |
| **QLogic Drivers** | • qlnativefc - 1.1.7.0-1OEM.550.0.0.1198610<br>• qla4xxx - 634.55.20.0-1vmw<br>• qlcnic - 5.5.164<br>• qlge - v3.00.00.57 |
| **Emulex Drivers** | • lpfc - 10.0.575.8-1OEM.550.0.0.1198611<br>• elxnet - 10.0.575.7-10EM- 550.0.0.1198611<br>• be2iscsi - 4.6.261.0 |
| **Dell Storage Controller Drivers** | • mpt2sas - 15.10.05.00.1vmw |

# 5 ESXi 5.1 Update 3 image customization details

Table 8 ESXi 5.1 Update 3 revision A00 image customization details

| | |
|---|---|
| **Product Name** | Dell Customized VMware ESXi 5.1 Update 3 Image |
| **Version** | A00 |
| **Build Number** | 2323236 |
| **File Name** | VMware-VMvisor-Installer-5.1.0.update03-2323236.x86_64-Dell_Customized_RecoveryCD_A00 .iso |
| **Release Date** | Dec 12, 2014 |
| **Dell Modified Files** | • etc/vmware/oem.xml<br>• etc/vmware/support |
| **Broadcom Drivers** | • tg3 - 3.137d.v50.1<br>• bnx2 - 2.2.5f.v50.9<br>• bnx2x - 2.711.10.v50.6<br>• cnic - 2.711.10.v50.2<br>• cnic-register - 1.711.10.v50.2<br>• bnx2fc - 1.711.10.v50.3<br>• bnx2i - 2.711.10.v50.2 |
| **Intel Drivers** | • igb - 5.2.7<br>• ixgbe - 3.21.5iov |
| **QLogic Drivers** | • qla2xxx - 934.5.45.0-1vmw<br>• qla4xxx - 644.5.35.0<br>• qlcnic - 5.3.191<br>• qlge - v2.00.00.59 |
| **Emulex Drivers** | • lpfc820 - 10.2.292.0<br>• be2iscsi - 10.2.250.0<br>• be2net - 10.2.453.0 |
| **Dell Storage Controller Drivers** | • mpt2sas - 20.00.00.00.1vmw<br>• megaraid-sas- 06.803.73.00<br>• megaraid-perc9 - 6.901.55.00.1vmw<br>• mpt3sas - 04.00.00.00.1vmw |
| **Brocade Drivers** | • bfa - 3.2.4.0<br>• bna - 3.2.4.0 |
| **Mellanox Drivers** | • mlx4_core - 1.9.9.0<br>• mlx4_en - 1.9.9.0 |
| **Micron Drivers** | • mtip32xx-scsi - 2.13.2 |

# 6 ESXi 5.1 Update 2 image customization details

Table 9 ESXi 5.1 Update 2 revision A04 image customization details

| | |
|---|---|
| **Product Name** | Dell Customized VMware ESXi 5.1 Update 2 Image |
| **Version** | A04 |
| **Build Number** | 2000251 |
| **File Name** | VMware-VMvisor-Installer-5.1.0.update02-2000251.x86_64-Dell_Customized_RecoveryCD_A04 .iso |
| **Release Date** | Dec 2, 2014 |
| **Dell Modified Files** | • etc/vmware/oem.xml<br>• etc/vmware/support |
| **Broadcom Drivers** | • tg3 - 3.137d.v50.1<br>• bnx2 - 2.2.5f.v50.6<br>• bnx2x - 2.710.39.v50.2<br>• cnic - 2.710.35.v50.5<br>• cnic-register - 1.710.30.v50.1<br>• bnx2fc - 1.710.35.v50.2<br>• bnx2i - 2.710.30.v50.4 |
| **Intel Drivers** | • igb - 5.2.7<br>• ixgbe - 3.21.5iov |
| **QLogic Drivers** | • qla2xxx - 934.5.38.0-1vmw<br>• qla4xxx - 644.5.34.0<br>• qlcnic - 5.3.191<br>• qlge - v2.00.00.59 |
| **Emulex Drivers** | • lpfc820 - 10.2.292.0<br>• be2iscsi - 10.2.250.0<br>• be2net - 10.2.293.0 |
| **Dell Storage Controller Drivers** | • mpt2sas - 19.00.00.00.1vmw<br>• megaraid-sas- 06.803.73.00<br>• megaraid-perc9 - 6.901.55.00.1vmw<br>• mpt3sas - 04.00.00.00.1vmw |
| **Brocade Drivers** | • bfa - 3.2.4.0<br>• bna - 3.2.4.0 |
| **Mellanox Drivers** | • mlx4_core - 1.9.9.0<br>• mlx4_en - 1.9.9.0 |
| **Micron Drivers** | • mtip32xx-scsi - 2.13.2 |

**Older revisions for ESXi 5.1 Update 2**

Table 10: ESXi 5.1 Update 2 Revision A03 Image Customization Details

Table 11: ESXi 5.1 Update 2 Revision A02 Image Customization Details

Table 12: ESXi 5.1 Update 2 Revision A01 Image Customization Details

Table 13: ESXi 5.1 Update 2 Revision A00 Image Customization Details

Table 10 ESXi 5.1 Update 2 revision A03 image customization details

| | |
|---|---|
| **Product Name** | Dell Customized VMware ESXi 5.1 Update 2 Image |
| **Version** | A03 |
| **Build Number** | 2000251 |
| **File Name** | VMware-VMvisor-Installer-5.1.0.update02-2000251.x86_64-Dell_Customized_RecoveryCD_A03 .iso |
| **Release Date** | Sep 9, 2014 |
| **Dell Modified Files** | • etc/vmware/oem.xml<br>• etc/vmware/support |
| **Broadcom Drivers** | • tg3 - 3.135b.v50.2<br>• bnx2 - 2.2.5d.v50.3<br>• bnx2x - 1.710.10.v50.1<br>• cnic - 1.78.76.v50.4<br>• cnic-register - 1.710.05.v50.3<br>• bnx2fc - 1.710.08.v50.1<br>• bnx2i - 2.710.03.v50.2 |
| **Intel Drivers** | • igb - 5.2.5<br>• ixgbe - 3.21.4iov |
| **QLogic Drivers** | • qla2xxx - 934.5.38.0-1vmw<br>• qla4xxx - 644.5.34.0<br>• qlcnic - 5.3.191<br>• qlge - v2.00.00.59 |
| **Emulex Drivers** | • lpfc820 - 10.2.292.0<br>• be2iscsi - 10.2.250.0<br>• be2net - 10.2.293.0 |
| **Dell Storage Controller Drivers** | • mpt2sas - 19.00.00.00.1vmw<br>• megaraid-sas- 06.802.71.00<br>• megaraid-perc9 - 6.901.55.00.1vmw<br>• mpt3sas - 04.00.00.00.1vmw |
| **Brocade Drivers** | • bfa - 3.2.4.0<br>• bna - 3.2.4.0 |
| **Mellanox Drivers** | • mlx4_core - 1.9.9.0<br>• mlx4_en - 1.9.9.0 |
| **Micron Drivers** | • mtip32xx-scsi - 2.12.1 |

Table 11 ESXi 5.1 Update 2 revision A02 image customization details

| | |
|---|---|
| **Product Name** | Dell Customized VMware ESXi 5.1 Update 2 Image |
| **Version** | A02 |
| **Build Number** | 1483097 |
| **File Name** | VMware-VMvisor-Installer-5.1.0.update02-1483097.x86_64-Dell_Customized_RecoveryCD_A02.iso |
| **Release Date** | July 1, 2014 |
| **Dell Modified Files** | • etc/vmware/oem.xml<br>• etc/vmware/support |
| **Broadcom Drivers** | • tg3 – 3.135b.v50.2<br>• cnic-register – 1.78.75.v50.1<br>• bnx2 – 2.2.4f.v50.3<br>• bnx2x – 1.78.79.v50.2<br>• cnic – 1.78.76.v50.4<br>• bnx2fc – 1.78.76.v50.1<br>• bnx2i – 2.78.76.v50.1 |
| **Intel Drivers** | • igb – 5.2.5<br>• ixgbe – 3.21.4iov |
| **QLogic Drivers** | • qla2xxx – 934.5.32.0-1vmw<br>• qla4xxx – 634.5.28.0<br>• qlcnic – 5.1.184<br>• qlge – v2.00.00.59 |
| **Emulex Drivers** | • lpfc820 – 0:10.0.727.24<br>• be2iscsi – 10.0.727.4401<br>• be2net – 10.0.727.28 |
| **Dell Storage Controller Drivers** | • megaraid-sas – 06.802.71.00<br>• mpt2sas – 19.00.00.00.1vmw<br>• megaraid_perc9 – 6.900.50.00.1vmw |
| **Brocade Drivers** | • bfa – 3.2.4.0<br>• bna – 3.2.4.0 |
| **Mellanox Drivers** | • mlx4_core - 1.9.9.0<br>• mlx4_en - 1.9.9.0 |
| **Micron Drivers** | • mtip32xx-scsi - 2.12.1 |

Table 12 ESXi 5.1 Update 2 revision A01 image customization details

| | |
|---|---|
| **Product Name** | Dell Customized VMware ESXi 5.1 Update 2 Image |
| **Version** | A01 |
| **Build Number** | 1483097 |
| **File Name** | VMware-VMvisor-Installer-5.1.0.update02-1483097.x86_64-Dell_Customized_RecoveryCD_A01.iso |
| **Release Date** | March 11, 2014 |
| **Dell Modified Files** | • etc/vmware/oem.xml<br>• etc/vmware/support |
| **Broadcom Drivers** | • tg3 – 3.135b.v50.1<br>• cnic-register – 1.78.50.v50.1<br>• bnx2 – 2.2.4d.v50.1<br>• bnx2x – 1.78.58.v50.1<br>• cnic – 1.78.53.v50.4<br>• bnx2fc – 1.78.51.v50.1<br>• bnx2i – 2.78.52.v50.1 |
| **Intel Drivers** | • igb – 5.0.5.1<br>• ixgbe – 3.14.3iov |
| **QLogic Drivers** | • qla2xxx – 934.5.29.0-1vmw<br>• qla4xxx – 634.5.26.0<br>• qlcnic – 5.1.171<br>• qlge – v2.00.00.57 |
| **Emulex Drivers** | • lpfc820 – 0:10.0.727.24<br>• be2iscsi – 10.0.727.4401<br>• be2net – 10.0.727.28 |
| **Dell Storage Controller Drivers** | • megaraid-sas – 06.802.71.00<br>• mpt2sas – 17.00.00.00.1vmw<br>• megaraid_perc9 – 6.900.50.00.1vmw |

Table 13 ESXi 5.1 Update 2 revision A00 image customization details

| | |
|---|---|
| **Product Name** | Dell Customized VMware ESXi 5.1 Update 2 Image |
| **Version** | A00 |
| **Build Number** | 1483097 |
| **File Name** | VMware-VMvisor-Installer-5.1.0.update02-1483097.x86_64-Dell_Customized_RecoveryCD_A00.iso |
| **Release Date** | Feb 24, 2014 |
| **Dell Modified Files** | • etc/vmware/oem.xml<br>• etc/vmware/support |
| **Broadcom Drivers** | • tg3 - 3.135b.v50.1<br>• cnic-register – 1.78.50.v50.1<br>• bnx2 – 2.2.4d.v50.1<br>• bnx2x – 1.78.58.v50.1<br>• cnic – 1.78.53.v50.4<br>• bnx2fc – 1.78.51.v50.1<br>• bnx2i – 2.78.52.v50.1 |
| **Intel Drivers** | • igb – 5.0.5.1<br>• ixgbe – 3.14.3iov |
| **QLogic Drivers** | • qla2xxx – 934.5.29.0-1vmw<br>• qla4xxx – 634.5.26.0<br>• qlcnic – 5.1.171<br>• qlge – v2.00.00.57 |
| **Emulex Drivers** | • lpfc820 – 0:8.2.4.151.65<br>• be2iscsi – 4.6.142.2<br>• be2net – 4.1.255.11 |
| **Dell Storage Controller Drivers** | • megaraid-sas – 06.801.52.00<br>• mpt2sas – 17.00.00.00.1vmw<br>• megaraid_perc9 – 6.900.50.00.1vmw |

# 7 ESXi 5.1 Update 1 image customization details

Table 14 ESXi 5.1 Update 1 revision A03 image customization details

| | |
|---|---|
| **Product Name** | Dell Customized VMware ESXi 5.1 Update 1 |
| **Version** | A03 |
| **Build Number** | 1065491 |
| **File Name** | VMware-VMvisor-Installer-5.1.0.update01-1065491.x86_64-Dell_Customized_RecoveryCD_A03.iso |
| **Release Date** | December 03, 2013 |
| **Dell Modified Files** | • etc/vmware/oem.xml<br>• etc/vmware/support |
| **Broadcom Drivers** | • tg3 – 3.131d.v50.1<br>• cnic–register – 1.78.1.v50.1<br>• bnx2 – 2.2.3t.v50.2<br>• bnx2x – 1.78.27.v50.1<br>• cnic – 1.78.12.v50.4<br>• bnx2fc – 1.78.16.v50.1<br>• bnx2i – 2.76.56.v50.2 |
| **Intel Drivers** | • igb – 4.2.16.3<br>• ixgbe – 3.14.3 |
| **QLogic Drivers** | • qla2xxx – 934.5.22.0–1vmw<br>• qla4xxx – 634.5.18.0–1vmw<br>• qlcnic – 5.1.157<br>• qlge – v2.00.00.54-04202012 |
| **Emulex Drivers** | • lpfc820 – 0:8.2.4.151.65<br>• be2iscsi – 4.6.142.2 |
| **Brocade Drivers** | • bna – 3.2.3.0<br>• bfa – 3.2.3.0 |
| **Dell Storage Controller Drivers** | • mpt2sas – 16.00.00.00.1vmw<br>• megaraid–sas – 06.801.52.00 |
| **Micron Drivers** | • mtip32xx-scsi-2.8.0 |

**Older revisions for ESXi 5.1 Update 1**

Table 15: ESXi 5.1 Update 1 Revision A02 Image Customization Details

Table 16: ESXi 5.1 Update 1 Revision A01 Image Customization Details

Table 17: ESXi 5.1 Update 1 Revision A00 Image Customization Details

Table 15 ESXi 5.1 Update 1 revision A02 image customization details

| | |
|---|---|
| **Product Name** | Dell Customized VMware ESXi 5.1 Update 1 Recovery Image |
| **Version** | A02 |
| **Build Number** | 1065491 |
| **File Name** | VMware–VMvisor–Installer–5.1.0.update01–1065491.x86_64Dell_Customized_RecoveryCD_A02.iso |
| **Release Date** | September 24, 2013 |
| **Dell Modified Files** | • etc/vmware/oem.xml<br>• etc/vmware/support |
| **Broadcom Drivers** | • tg3 – 3.131d.v50.1<br>• cnic–register –1.76.53.v50.1<br>• bnx2 – 2.2.3m.v50.4<br>• bnx2x – 1.76.54.v50.1<br>• cnic – 1.76.59.v50.1<br>• bnx2fc – 1.76.57.v50.1<br>• bnx2i – 2.76.56.v50.2 |
| **Intel Drivers** | • igb – 4.2.16.3<br>• ixgbe – 3.14.3 |
| **QLogic Drivers** | • qla2xxx – 934.5.22.0–1vmw<br>• qla4xxx – 634.5.18.0–1vmw<br>• qlcnic – 5.1.157<br>• qlge – v2.00.00.54-04202012 |
| **Emulex Drivers** | • lpfc820 – 0:8.2.4.151.65<br>• be2iscsi – 4.6.142.2 |
| **Brocade Drivers** | • bna – 3.2.1.1<br>• bfa – 3.2.1.1 |
| **Dell Storage Controller Drivers** | • mpt2sas – 16.00.00.00.1vmw<br>• megaraid–sas – 06.801.52.00 |
| **Micron Drivers** | • mtip32xx-scsi-2.4.10 |

Table 16 ESXi 5.1 Update 1 revision A01 image customization details

| | |
|---|---|
| **Product Name** | Dell Customized VMware ESXi 5.1 Update 1 Recovery Image |
| **Version** | A01 |
| **Build Number** | 1065491 |
| **File Name** | VMware-VMvisor-Installer-5.1.0.update01-1065491.x86_64Dell_Customized_RecoveryCD_A01.iso |
| **Release Date** | June 26, 2013 |
| **Dell Modified Files** | • etc/vmware/oem.xml<br>• etc/vmware/support |
| **Broadcom Drivers** | • tg3 - 3.129d.v50.1<br>• cnic-register -1.76.53.v50.1<br>• bnx2 - 2.2.3m.v50.4<br>• bnx2x - 1.76.54.v50.1<br>• cnic - 1.76.59.v50.1<br>• bnx2fc - 1.76.57.v50.1<br>• bnx2i - 2.76.56.v50.2 |
| **Intel Drivers** | • igb - 4.0.17<br>• ixgbe - 3.14.3 |
| **QLogic Drivers** | • qla2xxx - 934.5.20.0-1vmw<br>• qla4xxx - 634.5.18.0-1vmw<br>• qlcnic - 5.1.157<br>• qlge - v2.00.00.54-04202012 |
| **Emulex Drivers** | • lpfc820 - 0:8.2.4.146.62<br>• be2iscsi - 4.4.264.0 |
| **Brocade Drivers** | • bna - 3.2.0.0<br>• bfa - 3.2.1.0 |
| **Dell Storage Controller Drivers** | • mpt2sas - 16.00.00.00.1vmw<br>• megaraid-sas - 06.801.52.00 |
| **Micron Drivers** | • mtip32xx-scsi - 2.4.10 |

Table 17 ESXi 5.1 Update 1 revision A00 image customization details

| | |
|---|---|
| **Product Name** | Dell Customized VMware ESXi 5.1 Update 1 Recovery Image |
| **Version** | A00 |
| **Build Number** | 1065491 |
| **File Name** | VMware–VMvisor–Installer–5.1.0.update01–1065491.x86_64–Dell_Customized_RecoveryCD_A00.iso |
| **Release Date** | April 26, 2013 |
| **Dell Modified Files** | • etc/vmware/oem.xml<br>• etc/vmware/support |
| **Broadcom Drivers** | • tg3 – 3.129d.v50.1<br>• cnic–register – 1.76.53.v50.1<br>• bnx2 – 2.2.3m.v50.4<br>• bnx2x – 1.76.54.v50.1<br>• cnic – 1.76.59.v50.1<br>• bnx2fc – 1.76.57.v50.1<br>• bnx2i – 2.76.56.v50.2 |
| **Intel Drivers** | • igb – 4.0.17<br>• ixgbe – 3.14.3 |
| **QLogic Drivers** | • qla2xxx – 934.5.20.0–1vmw<br>• qla4xxx – 634.5.18.0–1vmw<br>• qlcnic – 5.1.157<br>• qlge – 2.0.0.54 |
| **Emulex Drivers** | • lpfc820 – 0:8.2.4.146.62<br>• be2iscsi – 4.4.264.0 |
| **Brocade Drivers** | • bna – 3.2.0.0<br>• bfa – 3.2.0.0 |
| **Dell Storage Controller Drivers** | • mpt2sas – 16.00.00.00.1vmw |
| **Micron Drivers** | • mtip32xx-scsi – 2.4.10 |

# 8 ESXi 5.1 image customization details

Table 18 ESXi 5.1 revision A01 image customization details

| | |
|---|---|
| **Product Name** | Dell Customized VMware ESXi 5.1 Recovery Image |
| **Version** | A01 |
| **Build Number** | 799733 |
| **File Name** | VMware–VMvisor–Installer–5.1.0–799733.x86_64–Dell_Customized_RecoveryCD_A01.iso |
| **Release Date** | December 18, 2012 |
| **Dell Modified Files** | • etc/vmware/oem.xml<br>• etc/vmware/support |
| **Broadcom Drivers** | • tg3 – 3.124c.v50.1<br>• bnx2 – 2.2.3e.v50.1<br>• bnx2x – 1.74.17.v50.1<br>• cnic – 1.74.04.v50.1<br>• cnic–register – 1.72.1.v50.2<br>• bnx2fc – 1.74.02.v50.2<br>• bnx2i – 2.74.05.v50.1 |
| **Intel Drivers** | • igb – 3.4.7.3 |
| **QLogic Drivers** | • qla2xxx – 911.k1.1–26vmw<br>• qla4xxx – 624.01.43–1vmw<br>• qlcnic – 5.0.750<br>• qlge – v2.0.0.54–0420202012 |
| **Emulex Drivers** | • lpfc820 – 0:8.2.4.141.55<br>• be2iscsi – 4.2.324.12 |
| **Brocade Drivers** | • bna – 3.1.0.1<br>• bfa – 3.1.0.1 |
| **Dell Storage Controller Drivers** | • mpt2sas – 14.00.00.00.1vmw |

**Older revisions for ESXi 5.1**

Table 19: ESXi 5.1 Revision A00 Image Customization Details

Table 19 ESXi 5.1 revision A00 image customization details

| | |
|---|---|
| **Product Name** | Dell Customized VMware ESXi 5.1 Recovery Image |
| **Version** | A00 |
| **Build Number** | 799733 |
| **File Name** | VMware–VMvisor–Installer–5.1.0–799733.x86_64–Dell_Customized_RecoveryCD_A00.iso |
| **Release Date** | October 9, 2012 |
| **Dell Modified Files** | • etc/vmware/oem.xml<br>• etc/vmware/support |
| **Broadcom Drivers** | • tg3 – 3.123b.v50.1<br>• bnx2 – 2.2.1l.v50.1<br>• bnx2x – 1.72.54.v50.2<br>• cnic – 1.72.50.v50.1<br>• cnic–register – 1.72.1.v50.1<br>• bnx2fc – 1.72.51.v50.1<br>• bnx2i – 2.72.10.v50.2 |
| **Intel Drivers** | • igb – 3.4.7.3 |
| **QLogic Drivers** | • qla2xxx – 911.k1.1–26vmw<br>• qla4xxx – 624.01.43<br>• qlcnic – 5.0.746<br>• qlge – v2.0.0.54–0420202012 |
| **Emulex Drivers** | • lpfc820 – 0:8.2.3.1–127vmw<br>• be2iscsi – 4.1.334.3 |
| **Brocade Drivers** | • bna – 3.1.0.0<br>• bfa – 3.1.0.0 |
| **Dell Storage Controllers Drivers** | • mpt2sas – 14.00.00.00.1vmw |

# 9 ESXi 5.0 Update 3 image customization details

Table 20 ESXi 5.0 Update 3 revision A00 image customization details

| | |
|---|---|
| **Product Name** | Dell Customized VMware ESXi 5.0 Update 3 |
| **Version** | A00 |
| **Build Number** | 1311175 |
| **File Name** | VMware-VMvisor-Installer-5.0.0.update03-1311175.x86_64-Dell_Customized_RecoveryCD_A00.iso |
| **Release Date** | October 30, 2013 |
| **Dell Modified Files** | • etc/vmware/oem.xml<br>• etc/vmware/support |
| **Broadcom Drivers** | • tg3 - 3.133d.v50.1<br>• cnic-register - 1.78.1.v50.1<br>• bnx2 - 2.2.3t.v50.2<br>• bnx2x - 1.78.27.v50.1<br>• cnic - 1.78.12.v50.4<br>• bnx2fc - 1.78.16.v50.1<br>• bnx2i - 2.78.11.v50.1 |
| **Intel Drivers** | • igb - 4.2.16.3<br>• ixgbe - 3.18.7iov |
| **Qlogic Driver Versions** | • qla2xxx - 934.5.29.0-1vmw<br>• qla4xxx - 634.5.18.0-1vmw<br>• qlcnic - 5.1.157<br>• qlge - v2.00.00.57 |
| **Emulex Drivers** | • lpfc820 - 0:8.2.4.151.65<br>• be2iscsi - 4.6.142.2<br>• be2net - 4.6.142.10 |
| **Brocade Drivers** | • bna - 3.2.3.0<br>• bfa - 3.2.3.0 |
| **Dell Storage Controllers Drivers** | • mpt2sas - 16.00.00.00.1vmw |

# 10 ESXi 5.0 Update 2 image customization details

Table 21 ESXi 5.0 Update 2 revision A01 image customization details

| | |
|---|---|
| **Product Name** | Dell Customized VMware ESXi 5.0 Update 2 Recovery Image |
| **Version** | A01 |
| **Build Number** | 914586 |
| **File Name** | VMware–VMvisor–Installer–5.0.0.update2–914586.x86_64–Dell_Customized_RecoveryCD_A01.iso |
| **Release Date** | June 26, 2013 |
| **Dell Modified Files** | • etc/vmware/oem.xml<br>• etc/vmware/support |
| **Broadcom Drivers** | • tg3 - 3.129d.v50.1<br>• cnic-register -1.76.53.v50.1<br>• bnx2 - 2.2.3m.v50.4<br>• bnx2x - 1.76.54.v50.1<br>• cnic - 1.76.59.v50.1<br>• bnx2fc - 1.76.57.v50.1<br>• bnx2i - 2.76.56.v50.2 |
| **Intel Drivers** | • igb - 4.0.17<br>• ixgbe - 3.14.3iov |
| **Qlogic Driver Versions** | • qla2xxx - 934.5.20.0-1vmw<br>• qla4xxx - 634.5.18.0-1vmw<br>• qlcnic - 5.1.157<br>• qlge - v2.00.00.54-04202012 |
| **Emulex Drivers** | • lpfc820 - 0:8.2.4.146.62<br>• be2iscsi - 4.4.264.0<br>• be2net – 4.4.231.0 |
| **Brocade Drivers** | • bna - 3.2.0.0<br>• bfa - 3.2.1.0 |
| **Dell Storage Controllers Drivers** | • mpt2sas - 16.00.00.00.1vmw |
| **Micron Drivers** | • mtip32xx-scsi - 2.4.10 |

**Older revisions for ESXi 5.0 Update 2**

Table 22: ESXi 5.0 Update 2 Revision A00 Image Customization Details

Table 22 ESXi 5.0 Update 2 revision A00 image customization details

| | |
|---|---|
| **Product Name** | Dell Customized VMware ESXi 5.0 Update 2 Recovery Image |
| **Version** | A00 |
| **Build Number** | 914586 |
| **File Name** | VMware–VMvisor–Installer–5.0.0.update2–914586.x86_64–Dell_Customized_RecoveryCD_A00.iso |
| **Release Date** | January 17, 2013 |
| **Dell Modified Files** | • etc/vmware/oem.xml<br>• etc/vmware/support |
| **Broadcom Drivers** | • bnx2 – 2.2.3e.v50.1<br>• bnx2x – 1.74.19.v50.1<br>• bnx2i – 2.74.07.v50.1<br>• bnx2fc – 1.74.02.v50.2<br>• cnic – 1.74.04.v50.1<br>• tg3 – 3.124c.v50.1<br>• cnic–register – 1.72.1.v50.2 |
| **Intel Drivers** | • igb – 4.0.17<br>• ixgbe – 3.11.32 |
| **Qlogic Driver Versions** | • qlge – v2.00.00.54–04202012<br>• qlcnic – 5.0.750<br>• qla2xxx – 934.5.6.0–1vmw<br>• qla4xxx – 634.5.7.0–1OEM |
| **Emulex Drivers** | • lpfc820 – 0:8.2.4.141.55<br>• be2iscs – 4.2.324.12<br>• be2net – 4.2.327.0 |
| **Brocade Drivers** | • bna – 3.2.0.0<br>• bfa – 3.2.0.0 |
| **Dell Storage Controllers Drivers** | • mpt2sas – 15.00.01.00.1vmw |

# 11 ESXi 5.0 Update 1 image customization details

Table 23 ESXi 5.0 Update 1 revision A02 image customization details

| | |
|---|---|
| **Product Name** | Dell Customized VMware ESXi 5.0 Update 1 Recovery Image |
| **Version** | A02 |
| **Build Number** | 623860 |
| **File Name** | VMware–VMvisor–Installer–5.0.0.update1–623860.x86_64–Dell_Customized_RecoveryCD_A02.iso |
| **Release Date** | December 18, 2012 |
| **Dell Modified Files** | • etc/vmware/vmware.lic<br>• etc/vmware/oem.xml<br>• etc/vmware/support |
| **Broadcom Drivers** | • tg3 – 3.124c.v50.1<br>• bnx2 – 2.2.3e.v50.1<br>• bnx2x – 1.74.17.v50.1<br>• cnic – 1.74.04.v50.1<br>• cnic–register – 1.72.1.v50.2<br>• bnx2fc – 1.74.02.v50.2<br>• bnx2i – 2.74.07.v50.1 |
| **Intel Drivers** | • igb – 3.4.7.3<br>• ixgbe – 3.9.13.4–NAPI |
| **QLogic Drivers** | • qla2xxx – 911.k1.1–26vmw<br>• qla4xxx – 624.01.43–1vmw<br>• qlcnic – 5.0.750<br>• qlge – v2.00.00.54–04202012 |
| **Emulex Drivers** | • lpfc820 – 0:8.2.4.141.55<br>• be2iscsi – 4.2.324.12<br>• be2net – 4.2.327.0 |
| **Brocade Drivers** | • bna – 3.1.0.1<br>• bfa – 3.1.0.1 |
| **Dell Storage Controller Drivers** | • mpt2sas – 14.00.00.00.1vmw |

**Older revisions for ESXi 5.0 Update 1**

Table 24: ESXi 5.0 Update 1 Revision A01 Image Customization Details

Table 25: ESXi 5.0 Update 1 Revision A00 Image Customization Details

Table 24 ESXi 5.0 Update 1 revision A01 image customization details

| | |
|---|---|
| **Product Name** | Dell Customized VMware ESXi 5.0 Update 1 Recovery Image |
| **Version** | A01 |
| **Build Number** | 623860 |
| **File Name** | VMware-VMvisor-Installer-5.0.0.update1-623860.x86_64-Dell_Customized_RecoveryCD_A01.iso |
| **Release Date** | October 11, 2012 |
| **Dell Modified Files** | • etc/vmware/vmware.lic<br>• etc/vmware/oem.xml<br>• etc/vmware/support |
| **Broadcom Drivers** | • bnx2 – 2.2.1l.v50.1<br>• bnx2x – 1.72.54.v50.2<br>• bnx2i – 2.72.10.v50.2<br>• bnx2fc – 1.72.51.v50.1<br>• cnic – 1.72.50.v50.1<br>• tg3 – 3.123b.v50.1<br>• cnic–register – 1.72.1.v50.1 |
| **Intel Drivers** | • igb – 3.2.10<br>• ixgbe – 3.9.13–NAPI |
| **QLogic Drivers** | • qlge – v2.00.00.54–04202012<br>• qlcnic – 5.0.746<br>• qla2xxx – 911.k1.1–26vmw<br>• qla4xxx – 624.01.43–1vmw |
| **Emulex Drivers** | • lpfc820 – 0:8.2.2.126.50<br>• be2iscsi – 4.1.334.3<br>• be2net – 4.1.334.48 |
| **Brocade Drivers** | • bna – 3.1.0.0<br>• bfa – 3.1.0.0 |
| **Dell Storage Controller Drivers** | • mpt2sas – 13.10.02.00.1vmw |

Table 25 ESXi 5.0 Update 1 revision A00 image customization details

| | |
|---|---|
| **Product Name** | Dell Customized VMware ESXi 5.0 Update 1 Recovery Image |
| **Version** | A00 |
| **Build Number** | 623860 |
| **File Name** | VMware–VMvisor–Installer–5.0.0.update1–623860.x86_64–Dell_Customized_RecoveryCD_A00.iso |
| **Release Date** | June 26, 2012 |
| **Dell Modified Files** | • etc/vmware/vmware.lic<br>• etc/vmware/oem.xml<br>• etc/vmware/support |
| **Broadcom Drivers** | • bnx2 – 2.2.1j.v50.2<br>• bnx2x – 1.72.18.v50.4<br>• bnx2i – 2.72.10.v50.2<br>• bnx2fc –1.72.11.v50.1<br>• cnic – 1.72.9.v50.1<br>• tg3 – 3.123b.v50.1<br>• cnic – register – 1.72.1.v50.1 |
| **Intel Drivers** | • igb – 3.2.10<br>• ixgbe – 3.9.13–NAPI |
| **QLogic Drivers** | • qlge – v1.00.00.47–051711<br>• qlcnic – 5.0.741<br>• qla2xxx – 911.k1.1–26vmw<br>• qla4xxx – 624.01.43–1vmw |
| **Emulex Drivers** | • lpfc820 – 8.2.2.126.50<br>• be2iscsi – 4.1.334.3<br>• be2net – 4.1.334.0 |
| **Brocade Drivers** | • bna – 3.0.3.0<br>• bfa – 3.0.3.0 |
| **Dell Storage Controller Drivers** | • mpt2sas – 13.00.00.00.1vmw |

# 12 ESXi 5.0 image customization details

Table 26 ESXi 5.0 revision A04 image customization details

| | |
|---|---|
| **Product Name** | Dell Customized VMware ESXi 5.0 Recovery Image |
| **Version** | A04 |
| **Build Number** | 504890 |
| **File Name** | VMware–VMvisor–Installer–5.0.0–504890.x86_64–Dell_Customized_RecoveryCD_A04.iso |
| **Release Date** | June 26, 2012 |
| **Patches** | ESXi500–201111001.zip<br>See kb.vmware.com/kb/2008017 |
| **Dell Modified Files** | • etc/vmware/vmware.lic<br>• etc/vmware/oem.xml<br>• etc/vmware/support |
| **Broadcom Drivers** | • bnx2 – 2.2.1j.v50.2<br>• bnx2x – 1.72.18.v50.4<br>• bnx2i – 2.72.10.v50.2<br>• bnx2fc – 1.72.11.v50.1<br>• cnic – 1.72.9.v50.1<br>• tg3 – 3.123b.v50.1<br>• cnic–register 1.72.1.v50.1 |
| **Intel Drivers** | • igb – 3.2.10<br>• ixgbe – 3.9.13–NAPI |
| **QLogic Drivers** | • qlge – v1.00.00.47–051711<br>• qlcnic – 5.0.741<br>• qla2xxx – 911.k1.1–26vmw<br>• qla4xxx – 624–01–43 |
| **Emulex Drivers** | • lpfc820 – 0:8.2.2.126.50<br>• be2iscsi – 4.1.334.3<br>• be2net – 4.1.334.0 |
| **Brocade Drivers** | • bna – 3.0.3.0<br>• bfa – 3.0.3.0 |
| **Dell Storage Controller Drivers** | • megaraid–sas – 5.34<br>• mpt2sas – 13.00.00.00.1vmw |

**Older revisions for ESXi 5.0**

Table 27: ESXi 5.0 Revision A03 Image Customization Details

Table 28: ESXi 5.0 Revision A02 Image Customization Details

Table 29: TESXi 5.0 Revision A01 Image Customization Details

Table 30: ESXi 5.0 Revision A00 Image Customization Details

Table 27 ESXi 5.0 revision A03 image customization details

| | |
|---|---|
| **Product Name** | Dell Customized VMware ESXi 5.0 Recovery Image |
| **Version** | A03 |
| **Build Number** | 504890 |
| **File Name** | VMware–VMvisor–Installer–5.0.0–504890.x86_64–Dell_Customized_RecoveryCD_A03.iso |
| **Release Date** | July 03, 2012 |
| **Patches** | ESXi500–201111001.zip<br>See kb.vmware.com/kb/2008017 |
| **Dell Modified Files** | • etc/vmware/vmware.lic<br>• etc/vmware/oem.xml<br>• etc/vmware/support |
| **Broadcom Drivers** | • bnx2 – 2.2.12b.v50.3<br>• bnx2x – 1.70.34.v50.1<br>• bnx2i – 2.70.1k.v50.2<br>• bnx2fc – 1.0.1v.v50.1<br>• cnic – 1.11.18.v50.1<br>• tg3 – 3.120h.v50.2<br>• register–1.70.0.v50.9 |
| **Intel Drivers** | • igb – 3.2.10<br>• ixgbe – 3.17.13.–NAPI |
| **QLogic Drivers** | • qlge – v1.00.00.47–051711<br>• qlcnic – 5.0.736<br>• qla2xxx – 911.k1.1–19vmw<br>• qla4xxx – 624–01–36vmw |
| **Emulex Drivers** | • lpfc820 – 0:8.2.2.105.36<br>• be2iscsi – 4.0.317.1<br>• be2net – 4.0.355.1 |
| **Brocade Drivers** | • bna – 3.0.3.0<br>• bfa – 3.0.3.0 |
| **Dell Storage Controller Drivers** | • megaraid-sas–5.34 |

Table 28 ESXi 5.0 revision A02 image customization details

| | |
|---|---|
| **Product Name** | Dell Customized VMware ESXi 5.0 Recovery Image |
| **Version** | A02 |
| **Build Number** | 504890 |
| **File Name** | VMware–VMvisor–Installer–5.0.0–504890.x86_64–Dell_Customized_A02.iso |
| **Release Date** | 6 March, 2012 |
| **Patches** | ESXi500–201111001.zip<br>See kb.vmware.com/kb/2008017 |
| **Dell Modified Files** | • etc/vmware/vmware.lic<br>• etc/vmware/oem.xml<br>• etc/vmware/support |
| **Broadcom Drivers** | • tg3 – 3.120h.v50.2<br>• bnx2 – 2.1.12b.v50.3.<br>• bnx2x – 1.70.34.v50.1<br>• cnic – 1.11.18.v50.1<br>• cnic – register–1.70.0.v50.9<br>• bnx2fc – 1.0.1v.v50.1<br>• bnx2i – 2.70.1k.v50.2 |
| **Intel Drivers** | • igb – 3.2.10<br>• ixgbe – 3.7.13–NAPI |
| **QLogic Drivers** | • qla2xxx – 911.k1.1–19vmw<br>• qla4xxx – 624.01.36–1vmw<br>• qlcnic – 5.0.0.736<br>• qlge – v1.00.00.47–051711 |
| **Emulex Drivers** | • lpfc820 – 0:8.2.2.105.36<br>• be2iscsi – 4.0.317.1<br>• be2net – 4.0.355.1 |
| **Brocade Drivers** | • bna – 3.0.3.0<br>• bfa – 3.0.3.0 |
| **Dell Storage Controller Drivers** | • megaraid-sas – 5.34<br>• mpt2sas – 12.00.00.00.1vmw |

Table 29 ESXi 5.0 revision A01 image customization details

| | |
|---|---|
| **Product Name** | Dell Customized VMware ESXi 5.0 Recovery Image |
| **Version** | A01 |
| **Build Number** | 504890 |
| **File Name** | VMware–VMvisor–Installer–5.0.0–504890.x86_64–Dell_Customized_A01.iso |
| **Release Date** | December 19, 2011 |
| **Patches** | ESXi500–201111001.zip<br>See kb.vmware.com/kb/2008017 |
| **Dell Modified Files** | • etc/vmware/vmware.lic<br>• etc/vmware/oem.xml<br>• etc/vmware/support |
| **Intel Drivers** | • igb–3.1.17<br>• ixgbe–3.6.5–NAPI |
| **Qlogic Drivers** | • qla2xxx–911.k1.1–9vmw<br>• qla4xxx–624.01.32–1vmw<br>• qlge–v1.00.00.47–051711<br>• qlcnic–5.0.727 |
| **Emulex Drivers** | • lpfc820–0:8.2.2.105.36<br>• be2iscsi–4.0.317.1<br>• be2net–4.0.355.1 |
| **Brocade Drivers** | • bna–3.0.0.0<br>• bfa–3.0.0.0 |
| **Dell Storage Controller Drivers** | • megaraid–sas–5.34 |

Table 30 ESXi 5.0 revision A00 image customization details

| | |
|---|---|
| **Product Name** | Dell Customized VMware ESXi 5.0 Recovery Image |
| **Version** | A00 |
| **Build Number** | 469512 |
| **File Name** | VMware–VMvisor–Installer–5.0.0–469512.x86_64–Dell_Customized.iso |
| **Release Date** | October 10, 2011 |
| **Dell Modified Files** | • etc/vmware/oem.xml<br>• etc/vmware/support<br>• etc/vmware/vmware.lic |